

10GBASE-T

Copper SFP Transceiver



Features:

- Operating data rate up to 10G
- Compact RJ-45 connector assembly
- Single 3.3V power supply and Low power dissipation
- Hot Pluggable
- 10GBASE-T operation in the host systems with SGMII interface
- RoHS Compliant and Lead-Free
- Metal with lower EMI and excellent ESD performance
- Commercial operating temperature range: 0°C to +70°C , -40 °C ~ to 85°C



Applications:

- 10GBASE-T IEEE802.3an
- 1000BASE-T IEEE802.3ab
- 100BASE-TX IEEE802.3u
- 5G MGBASE-T
- 2.5G MGBASE-T

Product Description

The 10GBASE-T Copper SFP Transceiver is small form factor pluggable transceiver. They are compatible with SFP Multi- Sourcing Agreement (MSA) and comply with Gigabit Ethernet standard as specified in IEEE Std 802.3. They are compliant with RoHS and lead-free per Directive 2002/95/EC. The physical layer IC (PHY) can be accessed via I2C bus, allowing access to all PHY settings and features.

Ordering information

Part No.	Data Rate	Distance ^{*Note1}	Interface	Bail color	Temp. ^{*Note2}	DDMI
TCS-TGD0-01DCR	10G	30m	RJ45	NA	ST	Y
TCS-TGD0-01DIR	10G	30m	RJ45	NA	IT	Y

Note1: Over unshielded twisted pair (UTP) Category 5 Cable

Note2: ST: 0 ~ +75deg C ,IT:-40 ~ +85deg

Regulatory compliance

Feature	Standard	Performance
Electrostatic Discharge (ESD) to the Electrical Pins	MIL-STD-883G Method 3015.7	Class 1C (>1000 V)
Electrostatic Discharge to the enclosure	EN 55024:1998+A1+A2 IEC-61000-4-2 GR-1089-CORE	Compliant with standards
Electromagnetic Interference (EMI)	FCC Part 15 Class B EN55022:2006 CISPR 22B :2006 VCCI Class B	Compliant with standards Noise frequency range: 30 MHz to 6 GHz. Good system EMI design practice required to achieve Class B margins. System margins depend on customer host board and chassis design.
Immunity	EN 55024:1998+A1+A2 IEC 61000-4-3	Compliant with standards. 1kHz sine-wave, 80% AM, from 80 MHz to 1 GHz. No effect on transmitter/receiver performance is detectable between these limits.
Component Recognition	UL and CUL EN60950-1:2006	TUV Certificate No. E344594 (CB:JPTUV-053877)
RoHS2.0	2011/65/EU	Compliant with standards

Absolute Maximum Ratings^{*Note3}

Parameter	Symbol	Min	Max	Unit
Storage Temperature	TS	-40	+85	°C
Supply Voltage	V _{CC}	-0.5	4.0	V
Operating Humidity	-	5	95	%

Note3: Exceeding any one of these values may destroy the device permanently.

Recommended Operating Conditions

Parameter	Symbol	Min	Typical	Max	Unit
Power Supply Voltage	V _{CC}	3.13	3.30	3.47	V
Power Supply Current	I _{CC}	-	-	800	mA
Surge current	I _{surge}			30	mA
Case Operating Temperature	T _{op}	0	-	+70	°C
Case Operating Temperature	T _{op}	-40		85	°C
Data Rate (note4)	-		10		Gbps

Transmission Distance (note5)	-	30	m
-------------------------------	---	----	---

Low Speed Signals Electrical Characteristics

Parameter	Symbol	Min	Typ.	Max	Unit
Output LOW	V _{OL}	0	-	0.5	V
Output HIGH	V _{OH}	Host_Vcc-0.5	-	Host_Vcc+0.3	V
Input LOW	V _{IL}	0	-	0.8	V
Input HIGH	V _{IH}	2	-	Vcc+0.3	V

High Speed Electrical Interface, Transmission Line-SFP

Parameter	Symbol	Min	Typ.	Max	Unit
Symbol Rate Per Lane		-		800	Mbaud
Tx Output Impedance	Z _{Out}	90	100-	110	Ω
Rx Input Impedance	Z _{In}	90	100	110-	Ω

High Speed Electrical Interface, Host-SFP

Parameter	Symbol	Min	Typ.	Max	Unit
Differential data input swing	Z _{In}	500	-	2400	mV
Differential data Output swing	Z _{Out}	700	-	1600	mV
Waiting time For Restarting (note6)		-	-	10	us
Tx Input Impedance	Z _{In}	90	100-	110	Ω
Rx Output Impedance	Z _{Out}	90	100	110-	Ω

Note4. the module will operate as 1000BASE-T when the host system uses SERDES interface.

Note5. Over unshielded twisted pair (UTP) Category 5 Cable

Note6.From TX_Disable rising edge to Link Down

SFP Transceiver Electrical Pad Layout




Diagram of Host Board Connector Block Pin Numbers and Names

Pin Function Definitions:

Pin Num.	Name	Function
1	V _{ee} T	Transmitter Ground

2	TX Fault	Transmitter Fault(Note 7)
3	TX Disable	Transmitter Disable(Note 8)
4	MOD_DEF2	Module Definition 2 (Note 9)
5	MOD_DEF1	Module Definition 1 (Note 9)
6	MOD_DEF0	Module Definition 0 (Note 9)
7	RS0	No connect
8	LOS	Loss of Signal indication (Note 10)
9	RS1	No connect
10	V _{ee} R	Receiver Ground
11	V _{ee} R	Receiver Ground
12	RD-	Inverted Received Data Out (Note 11)
13	RD+	Non-inverted Received Data Out (Note 11)
14	V _{ee} R	Receiver Ground
15	V _{CCR}	Receiver Power Supply (Note 12)
16	V _{CCT}	Transmitter Power Supply (Note 12)
17	V _{ee} T	Transmitter Ground
18	TD+	Non-Inverted Transmit Data in (Note 13)
19	TD-	Inverted Transmit Data in (Note 13)
20	V _{ee} T	Transmitter Ground

Note7. Not Support and tied to GND within the module

Note8. TX disable is used to enable or disable PHY within the module.

Low (0 – 0.8V): PHY enabled ($>0.8, < 2.0V$): Undefined

High (2.0 – 3.465V): PHY Disabled Open: PHY Disabled

Note9. Mod-Def 0, 1, 2. These are the module definition pins. They should be pulled up to VCCT/VCCR through a 4.7K – 10K Ω resistor on the host board.

Mod-DEF0 is grounded by the module to indicate that the module is present

Mod-DEF1 is the clock line of two wire serial interface for serial ID

Mod-DEF2 is the data line of two wire serial interface for serial ID


Note10. Los is used as link indication feature for each rate.

Note11. RD-/+: These are the differential receiver outputs. They are AC coupled 100 Ω Differential lines which should be terminated with 100 Ω (differential) at host. The AC coupling is done inside the module and not be required on host.

Note12. VccR and VccT are the receiver and transmitter power supplies. They are defined as 3.3V \pm 5% at the SFP connector pin. Maximum supply current is 400 mA.

Note13. TD-/+: These are the differential transmitter inputs. They are AC coupled, Differential lines with 100 Ω differential termination inside the module. The AC coupling is done inside the module and not be required on host.

Mechanical Dimension



Obtaining Document

You can visit our website: <http://www.trixontech.com>

Or contact Trixon Inc. listed at the end of the documentation to get the latest document.

Notice

Trixon reserves the right to make changes to or discontinue any optical link product or service identified in this publication, without notice, in order to improve design and/or performance.

Applications that are described herein for any of the optical link products are for illustrative purposes only. Trixon makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Add: # 202, Section A, Building 1 No.209, Sanshe Road, Jinjiang District Industry Park Chengdu
610063. Sichuan P.R. CHINA

Tel: (+86) 028-85925400/Fax: (+86) 028-85925445

E-mail: info@trixontech.com

<http://www.trixontech.com>

© Copyright Trixon 2014 all rights reserved.

